

Monitoring

MDADM

Ustawiamy w pliku `/etc/mdadm/mdadm.conf`:

```
MAILADDR admin@domain.ltd
```

Należy wykonać restart MDADM Monitor:

```
/etc/init.d/mdadm restart
```

SMART

Instalacja:

```
aptitude install smartmontools
```

Edytujemy plik `/etc/default/smartmontools`:

```
enable_smart="/dev/sda /dev/sdb"

# uncomment to start smartd on system startup
start_smartd=yes

# uncomment to pass additional options to smartd on startup
smartd_opts="--interval=1800"
```

oraz `/etc/smartd.conf`:

```
DEVICESCAN -d removable -n standby -m admin@domain.ltd -M exec
/usr/share/smartmontools/smartd-runner
```

w przypadku sprzętowego kontrolera RAID:

```
/dev/sda -d megaraid,0 -n standby -m admin@domain.ltd -M exec
/usr/share/smartmontools/smartd-runner
/dev/sda -d megaraid,1 -n standby -m admin@domain.ltd -M exec
/usr/share/smartmontools/smartd-runner
```

Należy wykonać restart SMART Monitor:

```
/etc/init.d/smartmontools restart
```

Szczegóły dysku:

```
smartctl -a /dev/sda
```

From:

<https://kamil.kbejt.pl/> - **kamil.orchia.pl**

Permanent link:

<https://kamil.kbejt.pl/doku.php?id=monitoring&rev=1387726597>

Last update: **2025/01/11 18:57**

